

## AEG Series Emergency Light

LED 1.8W	100-240V AC
DC 3.7V	3H Emergency
Type 4X,IP66	-40 C ~ +55 C



### Applications

- Emergency lighting shall be installed at every exit door, at the intersection of corridors, at exit of aisles, at exit stairways or ramps and at such other locations and intervals as are necessary to provide the occupants with knowledge of the various means of egress available.
- Bugeye light is a kind of emergency light with two separate emergency bulb heads, “bugeye” means the shape of the light is like the eye of bug, you can call double lamp emergency light. SUREALL AEG series emergency light is famous for the long lasting emergency time and friendly–environment battery without no hazard to surroundings.
- Bug eye emergency light are applied for area where harsh conditions exits below:
  - > Inner workshop of non–hazardous products manufacturing, processing rooms, electrical control rooms
  - > Aisles or exit of storage and warehouse area for cartons
  - > Exit of machines maintenance areas, shit areas

### Features

SUREALL AEG series emergency light is designed with a bug eye shape to illuminate when failure or interrupt of power. This emergency lighting can be used as emergency light, emergency lamp, led emergency light, battery emergency, rechargeable emergency light, emergency light fixture, bug eye emergency light, led emergency lights with battery backup, battery operated emergency lights, bug eye lights, emergency night lights.

- > Bug eye shape twin lamp head for emergency lighting
- > Emergency long lasting time up to 180 min
- > Adjustable angle when wall mounted

### Technical Datasheet

Material	ABS
Rated Voltage	DC 3.7V
Charging Voltage	100–240V AC,50/60Hz
Wattage(W)	1.8W, 180Lm
Battery Capacity	Lithium 3.7V,1500mAh
Emergency Time	3H
IP Grade	Wet Locations, Type 4X, IP67
Ambient Temperature	-40°C~ +55°C /-40° F ~ +131° F
Size & Weight	280x280x78mm, 0.93Kg

### Mounting Options & Dimensions (mm/inch)

